



AC-8

NON-CONTACT AC VOLTAGE DETECTOR

- | Non-Contact Detection of AC Voltage 100~1000VAC (50/60Hz)
- | Rugged, double molded case
- | Used to find a break in a wire or detect the presence of voltage at outlets, lighting fixtures, circuit breakers, wires and cables
- | Bright LED and buzzer alarm if Voltage is present
- | Built-in bright flashlight with ON/OFF button
- | Convenient size with pocket clip
- | An essential tool for every electrician and tradesperson



Application

The Volt finder voltage detector is intended to check the presence of AC voltage. The presence of live voltage is signaled with a LED and Buzzer. Has Built-in bright flashlight with ON/OFF button and audible beeper indicator. Built-in Flashlight helps accessing dark areas.

This instrument confirms to CAT-III 1000V, CE.

General Specifications

Detection voltage range	100V AC to 1000 VAC, 24V AC to 1000V AC
Power	3V (AAA*2) alkaline battery
Operating temperature	-10°C to 50°C (14°F to 122°F)
Storage temperature	-10°C to 50°C (14°F to 122°F)
Humidity	95% {0°C to 30°C (32°F to 86°F)}
Altitude	3000m
Contaminated distinction	II
Weight	48.5g

Accessories

Battery, Instruction Manual.

Contact :

CEM INSTRUMENTS (INDIA) PVT. LTD.

32A, Ganesh Chandra Avenue, 4th Floor, Kolkata-700013

Tel: 033-22151376, 22159759

Email: info@cem-instruments.in / info@cem-india.com

Web: www.cem-instruments.in / www.cem-india.com

CEM INSTRUMENTS HEADQUATER & FACTORY

19th Building, 5th Region, Baiwangxin Industry Park,

Songbai Road, Baimang, Xili, Nanshan, Shenzhen,

China, 518108

Tel: +86-755-27353188, Fax: +86-755-27653699

